

## DIGITAL THERMO HYGROMETER



CODE 13711

Range from 0°C to 70°C (32°F to 158°F) and 20 to 99% humidity. Extra long cable (90 cm) enables flexible positioning of the sensor.

Instructions: In/Out: Temperature at device (In) and at sensor (Out). Min/Max: Minimum and maximum temperatures measured. Reset to zero: Press In/Out and Min/Max simultaneously for a short time. Note: Do not place in the direct surroundings from heat and humidification sources. Please remove batteries and dispose off them properly.

## ANALOGICAL THERMO HYGROMETER



CODE 13710

For precise monitoring of the temperature and humidity in a terrarium. Range from -20°C to 50°C and 0 to 100% humidity. Easy to mount due to sticker on the rear. Note: Do not mount in the direct vicinity of a heat or a humidification source.